

VIBRATION RANGE

ROCKET

Integrated electronic converter

The ROCKET is a plug and play integrated electronic converter that powers a high frequency vibrator.



- Converter weight: 3.4kg
- Vibration frequency 12,000 v.p.m.
- Optional rubber poker end
- Standard voltage/frequency input: 230v~50/60Hz (Optionally available in 110v~50/60Hz, upon request)
- Progressive start to avoid current peaks, preventing deterioration
- Bicolor external LED indicator to communicate any incident to the user
- Optional PRCD protection system that immediately disconnects the machine if there is a current leakage of 10mA



+ Plug & Play

Converter and poker integrated in a ready-to-use kit.

+ Zero maintenance

No spare parts required. No waste generation or periodic maintenance needs.

+ Light and compact

Lightweight and manageable, can be used in places of difficult access and handled by a single operator.

+ Safe and reliable

Hermetic protective housing that protects it against water and dust (IP67). Electrical protection against overloads, overvoltage, short circuits...



Technical Data

MODEL	Total weight (kg)	Length (m)	Diameter (mm)	Power of input (kW)	Performance (m3/h)
ROCKET 230V-38	14.6	370	38	0.75	Up to 20
ROCKET 230V-50	18.6	365	50	1.1	Up to 30
ROCKET 230V-60	20.6	420	58	1.5	Up to 35